

# TR-DCA1A4-XXA 直流電流傳送器



勝特力材料 886-3-5753170  
 勝特力电子(上海) 86-21-34970699  
 勝特力电子(深圳) 86-755-83298787  
[Http://www.100y.com.tw](http://www.100y.com.tw)

- 測量範圍：DC 200uA , 2mA , 20mA , 200mA , 2A , 5A
- 六種不同測量範圍之機種供選擇
- 輸出：直流 4 ~ 20mA
- 工作電壓：AC90V ~ 264V(50/60HZ)
- 外部調整：歸零及斜率調整

<b>Measure Range</b>	TR-DCA1A4-200UA : 0 - 200 uA DC TR-DCA1A4-2MA : 0 - 2 mA DC TR-DCA1A4-20MA : 0 - 20 mA DC TR-DCA1A4-200MA : 0 - 200 mA DC TR-DCA1A4-2A : 0 - 2 A DC TR-DCA1A4-5A : 0 - 5 A DC
<b>Output</b>	4 - 20 mA

	<p>TR-DCA1A4-200UA : 0 uA DC = 4 mA , 100 uA DC = 12 mA , 200 uA DC = 20 mA</p> <p>TR-DCA1A4-2MA : 0 mA DC = 4 mA , 1 mA DC = 12 mA , 2 mA DC = 20 mA</p> <p>TR-DCA1A4-20MA : 0 mA DC = 4 mA , 10 mA DC = 12 mA , 20 mA DC = 20 mA</p> <p>TR-DCA1A4-200MA : 0 mA DC = 4 mA , 100 mA DC = 12 mA , 200 mA DC = 20 mA</p> <p>TR-DCA1A4-2A : 0 A DC = 4 mA , 1 A DC = 12 mA , 2 A DC = 20 mA</p> <p>TR-DCA1A4-5A : 0 A DC = 4 mA , 2.5 A DC = 12 mA , 5 A DC = 20 mA</p>
<b>External Adjustment</b>	<p>TR-DCA1A4-200UA : External 94 dB Cal. VR</p> <p>Orthrt ZERO VR , SPAN VR</p>
<b>Power Supply</b>	90 - 260 ACV/ 50 Hz/60 Hz
<b>Operation Temperature</b>	0 - 50 °C ( 32 - 122 °F)
<b>Operation Humidity</b>	Less than 80 %RH
<b>Accessory Included</b>	None
<b>Optional Accessories</b>	<p>TR-DCV1A4-200MV : ST 50A/50mV , ST 100A/50mV , ST 1000A/50mV</p> <p>Orthrt None</p>
<b>Mounting</b>	Din rail or Wall
<b>Case</b>	ABS plastic
<b>Others</b>	<p>TR-DCA1A4-200UA : Two wires input, 500 mA fuse</p> <p>TR-DCA1A4-2MA : Two wires input, 500 mA fuse</p> <p>TR-DCA1A4-20MA : Two wires input, 500 mA fuse</p> <p>TR-DCA1A4-200MA : Two wires input, 500 mA fuse</p> <p>TR-DCA1A4-2A : Two wires input, 2 Amp fuse</p> <p>TR-DCA1A4-5A : Two wires input, 6 Amp fuse</p>