



# Charger Indicator



勝特力材料 886-3-5753170  
 勝特力电子(上海) 86-21-34970699  
 勝特力电子(深圳) 86-755-83298787  
[Http://www.100y.com.tw](http://www.100y.com.tw)

Dimension: 60x 44x 26mm (L x W x H)

## Specification

- AC input range..... 100~240VAC/0.5A
- Input frequency.....47~63Hz
- Inrush current.....cold start,<30A peak@115VAC
- Setup, hold up time.....400ms, 10ms@full load and 115VAC
- Overload protection.....pulsing mode, auto recovery
- Over voltage protection.....105% ~ 145%
- Operation temperature.....0-30°C @100%, 40°C @60% load
- Withstand voltage.....I/P-O/P:3.0KVAC,1min.
- Safety standards.....design refer to UL 1950,CSA 22.2
- EMC standards.....design refer to EN55022, EN50082-1
- Humidity.....20%~90%RH
- Length of output cable.....180cm of #2468,22AWGx 2C
- When you recharger the battery the light is red.  
 Until the battery is full the light turn green

MODEL	OUTPUT	
	VOLTAGE (V)	CURRENT (mA)
BC-A1	DC6V	500mA
BC-A2	DC9V	500mA
BC-A3	DC12V	500mA