







Hand tools

Crimping tools

Crimping tools

Terminals and parts model number in alphabetical order	Hand tools				Hand tools		Extraction and Insertion tools	
	for chain terminals	for loose piece terminals			for loose piece terminals		Extraction tool	Insertion tool
	YRS series	YC series	YRM series	YRF series	WC & JUC series JUK's Hand Tools	Terminal in loose form model No.		
	 Dimensions: (W x L) 59X224mm (2.3" x 8.8")	 Dimensions: (W x L) 70X296mm (2.8" x 11.7")	 Dimensions: (W x L) 59X224mm (2.3" x 8.8")	 Dimensions: (W x L) 70X295mm (2.8" x 11.6") 80X305mm (3.1" x 12.0")	勝特力材料 886-3-5753170 勝特力电子(上海) 86-21-34970699 勝特力电子(深圳) 86-755-83298787 Http://www.100y.com.tw			
<p>Note: (1) These tools are for prototype tooling or repair. (2) YC tool has two crimping sections (A and B). YRS tool has also two crimping sections by inverting upper dies. Be sure to check applicable wires before use. Since the dies are fixed, the crimping height cannot be adjusted. Therefore, some of the applicable wires described in this catalog may not be crimped properly. Before use, check for proper crimping (such as tensile strength, terminal/contact deformation). (3) These tools are not applicable to 2-wire crimping. (4) When hand crimping board-in terminals (SAN, SCN, SDN, SGN, SIN, SJN, SZN), care should be taken not to contaminate the solder tails of the terminals, as with greasy or oily fingers. If a solder problem arises, some cleaning of the lips of the terminal is advisable. (5) WC and JUC hand tools are provided by J.S.T.(U.K.) LTD. and contact them about the details of these hand tools.</p>								
CN-SAP/S1	YRS-870	-	-	-	-	-	-	-
JK-SP2***	YRS-370	-	-	-	-	-	KEJ-0.7	-
JK-SS2***	YRS-370	-	-	-	-	-	KEJ-0.4	-
J-SP1***	YRS-440	YC-440	-	-	-	J-BP1***	DEJ-0.3	-
J-SS1***	YRS-440	YC-440	-	-	-	J-BP1***	DEJ-0.3	-
J-SP2***	YRS-330	-	-	-	-	-	DEJ-0.3	-
J-SS2***	YRS-330	-	-	-	-	-	DEJ-0.3	-
LFO-1.0-250N	-	-	-	-	JUCS-FO	-	-	-
LFO-2.5-250N	-	-	-	-	JUCS-FO	-	-	-
MD-SP12**	YRS-470	-	-	-	-	-	MEJ-06	-
MD-SP22**	YRS-460	-	-	-	-	-	MEJ-06	-
RA-SC1290	YRS-231	-	YRM-232 (for AWG #26, #24) YRM-233 (for AWG #24, #22)	-	-	RA-BC12**	EJ-RA	-
RF-SC22**	-	-	YRM-230	-	-	RF-BC22**	-	-
RPJ-SP/SS2331	YRS-331	-	-	-	-	-	-	-
UBB-SP1110	YRS-951	-	-	-	-	-	-	-
UBB-SP2110	YRS-950	-	-	-	-	-	-	-
SAA-21(T)-**	-	YC-141	-	-	-	LAA-21(T)-**	-	-
SAA-50(T)-**	-	YC-182	-	-	-	LAA-50(T)-**	-	-
SAA-51(T)-**	-	YC-142	-	-	-	LAA-51(T)-**	-	-
SAB-51(T)-**	-	YC-142	-	-	-	LAB-51(T)-**	-	-
SAGH-002GU-P0.3	YRS-858	-	-	-	-	-	-	-
SAN-002T-0.8A	YRS-220	-	-	-	-	-	EJ-PH	-
SAN-002T-0.8K	YRS-220	-	-	-	-	-	EJ-PH	-
SBH-001T-P0.5	-	YC-670R	-	-	WC-670	BBH-001T-P0.5	-	-
SBHL-002T-P0.5	YRS-857	-	-	-	-	-	-	-
SBHM-001T-P0.5	-	YC-670R	-	-	-	BBHM-001T-P0.5	-	-
SBHS-002T-P0.5A	YRS-852	-	-	-	-	-	-	-
SBHSM-002T-P0.5	YRS-854	-	-	-	-	-	-	-

Crimping tools

Crimping tools

Terminals and parts model number in alphabetical order	Hand tools					Hand tools		Extraction and Insertion tools	
	for chain terminals	for loose piece terminals				for loose piece terminals		Extraction tool	Insertion tool
	YRS series	YC series	YRM series	YRF series	WC & JUC series JUC's Hand Tools	Terminal in loose form model No.			
SBHT-002T-P0.5	YRS-856 (UL3443 AWG #28, UL3239 AWG #24) YRS-857 (UL3443 AWG #26, UL10267 AWG #26)	-	-	-	-	-	-	EJ-BHT	IT-BHT
SCN-001T-1.0K	YRS-191	YC-191R	-	-	-	WC-191	BCN-001T-1.0K	-	-
SCN-001T-P1.0	YRS-191	YC-191R	-	-	-	WC-191	BCN-001T-P1.0	-	-
SCS-41T-2.3	-	-	-	-	-	-	-	CSJ-23	-
SCZH-002T-P0.5	YRS-492	-	-	-	-	-	-	-	-
SDF-01T-1.0A	-	YC-045	-	-	-	-	LDF-01T-1.0A	-	-
SDF-01T-1.3AS	-	YC-045	-	-	-	-	LDF-01T-1.3AS	-	-
SDN-21T-P1.5	-	YC-600R	-	-	-	-	BDN-21T-P1.5	-	-
SDY-01T-P1.6ASV	-	YC-525R	-	-	-	-	-	SLJ-1.4	-
SEH-001T-P0.6	YRS-260	YC-260R	-	-	-	WC-260	BEH-001T-P0.6	-	-
SF3F-002GF-P2.0	-	-	-	YRF-882	-	-	BF3F-002GF-P2.0	EJ-JFAJ3	-
SF3F-01GF-P2.0	-	-	-	YRF-881	-	-	BF3F-01GF-P2.0	EJ-JFAJ3	-
SF3M-01GF-M2.0N	-	-	-	YRF-881	-	-	BF3M-01GF-M2.0N	EJ-JFAJ3	-
SF3F-41GF-P2.0	-	-	-	YRF-880	-	-	LF3F-41GF-P2.0	EJ-JFAJ3	-
SF3M-41GF-M2.0N	-	-	-	YRF-880	-	-	LF3M-41GF-M2.0N	EJ-JFAJ3	-
SF3F-71GF-P2.0	-	-	-	YRF-1070	-	-	BF3F-71GF-P2.0	-	-
SF3M-71GF-M2.0N	-	-	-	YRF-1071	-	-	BF3M-71GF-M2.0N	-	-
SFO-41(T)-187N	-	YC-271	-	-	-	-	LFO-41(T)-187N	-	-
SFO-61(T)-250A	-	YC-270	-	-	-	-	LFO-61(T)-250A	-	-
SFPS-61(T)-250	-	YC-272	-	-	-	-	LFPS-61(T)-250	-	-
SFT-61T-250N	-	YC-510	-	-	-	-	LFT-61T-250N	-	-
SGF-41(T)-4	-	YC-055	-	-	-	-	LGF-41(T)-4	-	-
SGF-51(T)-5	-	YC-065	-	-	-	-	LGF-51(T)-5	-	-
SGF-51(T)-5A	-	YC-065	-	-	-	-	LGF-51(T)-5A	-	-
SGM-51(T)-4	-	YC-056	-	-	-	-	LGM-51(T)-4	-	-
SGM-51(T)-5	-	YC-056	-	-	-	-	LGM-51(T)-5	-	-
SHCM-A03T-P025	YRS-960	-	-	-	-	WC-SHCM-A03	-	-	-
SHF-001T-0.8BS	YRS-122	YC-122R	-	-	-	WC-122	BHF-001T-0.8BS	-	-
SHF-002T-0.8BS	YRS-300	-	-	-	-	-	-	-	-
SHR-001T-P0.6	YRS-580	YC-580R	-	-	-	-	BHR-001T-P0.6	-	-
SIM-01(T)-110A	-	YC-054	-	-	-	-	LIM-01(T)-110A	-	-
SIM-1.0-250D/N	-	-	-	-	-	JUCS-IM	-	-	-
SIM-2.5-250D/N	-	-	-	-	-	JUCS-IM	-	-	-
SIM-41(T)-110B	-	YC-067	-	-	-	-	LIM-41(T)-110B	-	-
SIM-51(T)-250N	-	YC-321	-	-	-	-	LIM-51(T)-250N	-	-
SIN-001T-1.2	YRS-034	-	-	-	-	-	-	-	-
SIN-002T-1.0S	YRS-035	-	-	-	-	-	-	-	-
SIN-01T-1.2	-	YC-340R	-	-	-	-	LIN-01T-1.2	-	-
SIN-01T-1.8	-	YC-032	-	-	-	-	LIN-01T-1.8	-	-
SIN-21T-1.8	-	YC-350	-	-	-	-	LIN-21T-1.8	-	-
SIN-21T-1.8S	-	YC-570 (for UL1015 AWG #22, #20) YC-571 (for UL1015 AWG #18)	-	-	-	-	LIN-21T-1.8S	-	-
SIN-61T-2.6S	-	YC-560 (for UL1015 AWG #14)	-	-	-	-	LIN-61T-2.6S	-	-