

Digital Regulated * DC Power Supply

Twintex

勝特力材料 886-3-5753170
勝特力电子(上海) 86-21-54151736
勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)

TP-3303
系列



功能特點

- 具有四組記憶儲存功能
- 具有面板鎖定功能
- 可預設電壓電流及密碼設定功能
- 具有輸出開關功能
- 第三組輸出可選擇2.5V, 3.3V, 5V/3A(限TP-3303)
- 定電壓, 定電流, 低紋波雜訊
- 可在機器內部設定串並聯模式
- 環型變壓器設計, 體積小, 重量輕

CE

MODEL NAME	TP-3303	TP-3305	TP-3602
Output	0~32V / 3Ax2	0~30V / 5Ax2	0~60V / 2Ax2
Constant Voltage Operation			
Line Regulation	CV≤0.01%+3mV	CV≤0.02%+3mV	CV≤0.02%+5mV
Load Regulation	CV≤0.01%+3mV	CV≤0.02%+5mV	CV≤0.02%+5mV
Recovery Time	≤100uS (50% load change,minimum load 0.5A)		
Ripple & Noise	≤2mV rms(5Hz~1MHz)	≤2mV rms(5Hz~1MHz)	≤2mV rms(5Hz~1MHz)
Temperature	≤300ppm/°C		
Constant Cruent Operation			
Line Regulation	CC≤0.2%+3mA	CC≤0.3%+3mA	CC≤0.3%+3mA
Load Regulation	CC≤0.2%+3mA	CC≤0.3%+5mA	CC≤0.3%+3mA
Ripple & Noise	≤3mA rms		
Tracking Parallel Operation			
Line Regulation	CV≤0.01%+3mA	CV≤0.05%+3mA	CV≤0.05%+5mA
Load Regulation	CV≤0.01%+3mA	CV≤0.05%+5mA	CV≤0.05%+5mA
Tracking Series Operation			
Line Regulation	CV≤0.01%+3mA		
Load Regulation	CV≤300mV		
Regulation	Line regulation≤5mV		Load regulation≤15mV
Rippie & Noise	≤2mV rms		
Voltage Range	2.5V, 3.3V, 5V (selectable)		
Output Current	3A		
Insulation degree	between base and output terminal≥ 20 Mohm/500VDC between base and power cord≥ 30 Mohm/500VDC		
Display Accuracy	3 & 1/2 digits LED display ≤±0.5%+2d		
Weight	7.0kg	8.0kg	8.0kg

TP-3303 系列

Specification