

Exciter

Sound Reproduction Lamps

勝特力材料 886-3-5753170
勝特力电子(上海) 86-21-54151736
勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)



image

P30d Base

Lamp Type	ANSI	Rated Voltages (V)	Amp.	Outside Dimension			Total Lumen (lm)	Avg Life (H)	Filament	Fig.No.
				A	B	C				
				BGK 4V 0.75A	BGK	4				

P30s Base

Lamp Type	ANSI	Rated Voltages (V)	Amp.	Outside Dimension			Total Lumen (lm)	Avg Life (H)	Filament	Fig.No.
				A	B	C				
				BRS 4V 0.75A	BRS	4				
BAK 4V 0.75A	BAK	4	0.75	16	50	28.5	30	200	C-6	2
BRK 4V 0.75A	BRK	4	0.75	16	60	28.5	30	50	C-8	5
BSK 6V 1A	BSK	6	1	16	50	28.5	70	100	C-6	2
BSS/BSB 6V 1A	BSS/BSB	6	1	16	55	28.5	70	100	C-8	5
BSW 7V 0.2A	BSW	7	0.2	16	55	28.5	13	50	C-8	5
BXN 10V 5A	BXN	10	5	25	78	37.5	900	100	C-6	2
BXB 8.5V 4A	BXB	8.5	4	25	78	41.3	680	100	C-8	5

BA15s Base

Lamp Type	ANSI	Rated Voltages (V)	Amp.	Outside Dimension			Total Lumen (lm)	Avg Life (H)	Filament	Fig.No.
				A	B	C				
				BXC 8.5V4A	BXC	8.5				
BXR 10V5A	BXR	10	5	25	78	40.5	900	100	C-6	3
BXG 10V7.5A	BXG	10	7.5	25	75	40.5	1700	100	C-6	3
BXE 10V7.5A	BXE	10	7.5	25	75	40.5	1700	100	C-8	4