


RIG-F型微波功率衰减器


■ 外形图：




图一




图二



图二



图三



图四



■ 衰减器

勝特力材料 886-3-5753170
 勝特力电子(上海) 86-21-34970699
 勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)

产品型号	额定功率 (W)	外形尺寸								频率 (Ghz)	驻波比 (VSWR≤)	
		图示	A±0.2	B±0.2	C±0.15	D	H	G	W±0.2			Φ
RIG-F	5	图二	10.8	6	8.5	6	1.7	2.7	1	2.7	3	1.2
RIG-F	10	图三	16	6	13	6	1.7	2.7	1	2.2	3	1.2
RIG-3F	10	图四	20	8	14	10	2.3	2.8	2.3	3.2	0.4	1.4
RIG-F	20	图三	16	6	13	6	1.7	2.7	1	2.2	3	1.2
RIG-1F	30	图一	6	6			1	2.4	1		2	1.2
RIG-F	30	图三	16	6	13	6	1.7	2.7	1	2.2	3	1.2
RIG-2F	60	图一	9	6			1	2.4	1		2	1.2
RIG-F	60	图三	16	6	13	9	2.2	3.2	1	2.2	3	1.2
RIG-4F	100	图一	10	12			1.5	3	1.5		2	1.2
RIG-F1	100	图三	26.5	12	20.5	10	4.2	5.5	1.5	3.2	0.8	1.4
RIG-F2	100	图三	25	12	19	10	4.2	5.5	1.5	3.2	0.8	1.4
RIG-F3	100	图三	25	12	19	10	4.7	6	1.5	3.2	0.8	1.4
RIG-F	100	图三	16	6	13	9	2.2	3.2	1	2.2	3	1.2