

DC/AC Power Inverter



ONEUTTER

Modified Sine Wave - 100 & 150Watt

DC to AC Power Inverter features:

- Compact Size, Light Weight & High Efficiency
- Low Battery Auto Shutdown
- Low Battery Alarm
- Overload and Short Circuit Protection
- Input Polarity Reverse Protection by Fuse
- High Surge Current Capacity. Easy to Start for TV, Motors & Other Inductive Load

勝特力材料 886-3-5753170
 勝特力电子(上海) 86-21-34970699
 勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)

	Model Number	KV - 100	KV - 150
	Specifications		
	Voltage In	12VDC or 24VDC	
	Voltage Out	100V, 115V, 220V, 230V, 240VAC	
<p>OUTPUT RECEPTACLES</p>  <p>Type-1 Type-2 Type-3 Type-4 Type-5 Type-6 Type-7</p>	Continuous Power	100 W	150 W
	Peak Power	200 W	300 W
	Output Frequency	50Hz or 60Hz	
	No Load Current Draw	0.1 A	0.2 A
	Efficiency	> 90%	> 90%
	Fuse	15A	20A
	Weight	0.45 Kg	0.48 Kg