

DC/AC Power Inverter




ONEUTTER

Modified Sine Wave - 2500Watt

DC to AC Power Inverter features:

- Compact Size, Light Weight & High Efficiency
- Low Battery Auto Shutdown
- Low Battery Alarm
- Overload and Short Circuit Protection
- Input Polarity Reverse Protection by Fuse
- High Surge Current Capacity. Easy to Start for TV, Motors & Other Inductive Load

勝特力材料 886-3-5753170
 勝特力电子(上海) 86-21-34970699
 勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)

	Model Number	KV - 2500
	Specifications	
	Voltage In	12VDC (11 ~ 15VDC Range) 24VDC (22 ~ 30VDC Range) 48VDC (44 ~ 60VDC Range)
	Voltage Out	100V, 115V, 220V, 230V, 240VAC
<p>OUTPUT RECEPTACLES</p>  <p>Type-1 Type-2 Type-3 Type-4 Type-5 Type-6 Type-7</p>	Continuous Power	2500W
	Peak Power	5000W
	Output Frequency	50Hz or 60Hz
	No Load Current Draw	2.5A
	Efficiency	90%
	Fuse	35A x 8
	Weight	4.8 Kg
	Dimension	400 x 190 x 100mm (LxWxH)