

Technical Data Sheet

PRODUCT DESCRIPTION:	Electronic Cleaning Solvent Plus	DATE:	03/97
PRODUCT CODE:	ECSP	PAGES:	1

PRODUCT DESCRIPTION

Electronic Cleaning Solvent Plus is a fast-drying solvent specially formulated for the quick and efficient cleaning of electrical equipment. It replaces CFC solvents that were used in **Electrolube** products such as **ECs** which exhibited rapid cleaning and fast evaporation rates. ECSP is 100% Ozone Friendly.

A version is available with integral brush for removing stubborn deposits.

PRODUCT USE

Electrical contacts, tape heads, PCB's, components in electronic and video equipment, computers, optical and precision instruments, cameras etc. Product contains **flammable solvent** so do not spray onto live electrical equipment or other sources of ignition. Immerse surface to be cleaned or spray onto surface to excess and allow to evaporate. A brush or foam tipped bud may be used to remove any stubborn deposits.

FEATURES

- * Non-CFC, non-halogenated cleaning solvent will not attack the Ozone Layer.
- * Leaves a perfectly clean, dry surface - conventional solvents often leave greasy deposits which attract dust and dirt.
- * Harmless to most plastics, rubbers, elastomers, and surface coatings.
- * CO₂ propelled aerosol version available containing 20% more active cleaner, fitted with a 360 valve for use in any orientation.

TYPICAL PROPERTIES

Specific Gravity @ 20°C:	0.79
Inhalation Toxicity:	500 ppm
Flash Point:	-48°C
Residue on Evaporation:	<1ppm
Evaporation Rate:	1.5 (ether = 1)
Boiling Point:	36°C

PACKAGING

200ml Aerosol
200ml Aerosol with brush
400ml Aerosol
5 Litre Bulk

ORDER CODE

ECSP200D
ECSP200DB
ECSP400D
ECSP05L

Copyright Electrolube 1997

All information is given in good faith but without warranty. Properties are given as a guide only and should not be taken as a specification. Electrolube cannot be held responsible for the performance of its products within any application determined by the customer, who must satisfy themselves as to the suitability of the product.