

Projector

Projector Lamp



勝特力材料 886-3-5753170
 勝特力电子(上海) 86-21-54151736
 勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)

BA15s Base

Lamp Type	ANSI	Rated Voltages (V)	Power Consumption (W)	Outside Dimension			Total Lumen (lm)	Color Temp (K)	Avg Life (H)	Filament	Fig.No.
				A	B	C					
FP-8 120V 50W	CAS/CAN	120	50	25	78	35	775	2900	50	CC-13	1
FP-8 120V 75W	CBJ/CBC	120	75	25	78	35	1250	2950	50	CC-13	1
FP-8 12V 100W	BXT	12	100	25	78	35	2800	3250	25	CF-6	1
FP-8 120V 100W	CDS/CDX	100/120	100	25	78	35	1800	2970	50	CC-13	1
FP-8 1/2V 120V 100W	CDD	120	100	25	78	35	1800	2970	50	CC-2V	1
FP-8 220/250V 100W	CJW/CJT	220? 250	100	25	78	35	1500	2870	50	CC-13	1
FP-8 H2 120V 100W	CEM	120	120	25	78	35	1950	3000	200	CC-13	1
FP-8 100/120V 150W	CEW/CFC	100/120	150	25	90	35	2900	3000	50	CC-13	1
FP-8H3 120V 150W	CHK	120	150	25	90	35	2200	2850	300	CC-13	1
FP-8 220/250V 150W	CKK	220? 250	150	25	90	35	2700	2920	50	CC-13	1
FP-8 100/120V 200W	CGW/CGT	100/120	200	25	90	35	4400	3100	25	CC-13	1
FP-8 1/2 100/120V 300W	CLS/CLG	100/120	300	27	105	35	7400	3150	25	C-13	1
FP-8 1/2D 120V 300W	CMV/CMT	120	300	27	105	35	7300	3100	25	C-13D	1
FP-10S 8/1/2 100/120V 300W	CYC/CYM	100/120	300	29.5	81	35	7400	3150	25	C-13	1
FP-8 1/2 220/250V	CNP	220? 250	300	27	105	35	6600	3050	25	CC-13	1

300W												
FP-10S 220/250V 300W	BEL	220? 250	300	29.5	81	35	6600	3050	25	CC-13	1	

BA 15d Base

Lamp Type	ANSI	Rated Voltages (V)	Power Consumption (W)	Outside Dimension			Total Lumen (lm)	Color Temp (K)	Avg Life (H)	Filament	Fig.No.
				A	B	C					
BLC 120V30W	BLC	120	30	35	60	35	400	2775	50	CC-2V	2
FP-8 DC120V50W	CAW	120	50	25	78	35	775	2900	50	CC-13	3
FP-8/2V DC120V50W	CAJ/CAC	120	50	25	78	35	800	2900	50	CC-2V	3
FP-8 DC NC120V50W	CAX	120	50	25	78	35	775	2900	50	CC-13	4
FP-8 DC120V75W	CBX/CBS	120	75	25	78	35	1250	2950	50	CC-13	3
FP-8 DC120V100W	CEA/CEB	120	100	25	78	35	1800	2970	50	CC-13	3
FP-8/2V DC120V100W	CDJ	120	100	25	78	35	1800	2970	50	CC-2V	3
FP-8 1/2 DC120V300W	CLX/CMB	120	300	27	105	35	7400	3150	25	C-13	3

E26 Base

Lamp Type	ANSI	Rated Voltages (V)	Power Consumption (W)	Outside Dimension			Total Lumen (lm)	Color Temp (K)	Avg Life (H)	Filament	Fig.No.
				A	B	C					
FP-10 E 120V500W	CZS	120	500	32	135	76	12500	3200	25	C-13D	5
FP-20E/DMS 120V500W	DMS	120	500	64	144	76	13200	3200	50	C-13	6
FP-12 E 120V750W	DCX	120	750	38	144	76	19600	3200	25	C-13D	5
FP-20 E 120V750W	DPB	120	750	64	144	76	19500	3200	25	C-13D	6

P28s Base

Lamp Type	ANSI	Rated Voltages (V)	Power Consumption (W)	Outside Dimension			Total Lumen (lm)	Color Temp (K)	Avg Life (H)	Filament	Fig.No.
				A	B	C					
FP-10 100/120V200W	CVX/CVS	100/120	200	32	135	55.5	4400	3100	25	CC-13	7
FP-10 100/120V300W	CXY	100/120	300	32	135	55.5	7300	3100	25	C-13D	7

FP-10C-13 120V300W	CXK	120	300	32	135	55.5	7400	3150	25	C-13	7
FP-10 100/120V 500W	CZX/DAB	100/120	500	32	135	55.5	12500	3200	25	C-13D	7
FP-20 100/120V500W		100/120	500	64	144	55.5	12500	3200	25	C-13D	8
FP-20 50HL 120V500W	DMX	120	500	64	144	55.5	13200	3200	50	C-13	8
FP-20 H5 120V500W	DNW	120	500	64	144	55.5	10000	3050	500	C-13	8
FP-12 100/120V750W	DDB	100/120	750	38	144	55.5	19500	3200	25	C-13D	7
FP-12 H2 120V750W	DDY	120	750	38	144	55.5	17000	2950	200	C-13D	7
FP-12 H5 120V750W	DGH	120	750	38	144	55.5	15000	3050	500	C-13D	7
FP-20 120V750W	DPJ	120	750	64	144	55.5	19500	3200	25	C-13D	8
FP-2 H2 120V750W	BFE	120	750	64	144	55.5	17000	3000	200	C-13	8
FP-12 100/120V1000W	DFT	100/120	1000	38	144	55.5	27400	3250	25	C-13D	7
FP-12 NET 120V1000W	DFD	120	1000	38	144	55.5	31000	3350	10	C-13D	7
FP-20 100/120V1000W	DRS	100/120	1000	64	144	55.5	27400	3250	25	C-13D	8
FP-20 C-13 120V1000W	DRC/DRB	120	1000	64	144	55.5	28000	3200	50	C-13	8

E39 Base

Lamp Type	ANSI	Rated Voltages (V)	Power Consumption (W)	Outside Dimension			Total Lumen (lm)	Color Temp (K)	Avg Life (H)	Filament	Fig.No.
				A	B	C					
FP-20LM 100/120V1000W	DRW	100/120	1000	64	230	125	27400	3250	25	C-13D	9
FP-20LM C-13 120V1000W	DPT	120	1000	64	230	125	28000	3200	50	C-13	9

P30s Base

Lamp Type	ANSI	Rated Voltages (V)	Power Consumption (W)	Outside Dimension			Total Lumen (lm)	Color Temp (K)	Avg Life (H)	Filament	Fig.No.
				A	B	C					
FP-GT 8V50W	CXR/CXL	8	50	43	96	47	36	3200	25	C-6	10

P40s Base

				Outside						

勝特力材料 886-3-5753170
 勝特力电子(上海) 86-21-54151736
 勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)

Lamp Type	ANSI	Rated Voltages (V)	Power Consumption (W)	Dimension			Total Lumen (lm)	Color Temp (K)	Avg Life (H)	Filament	Fig.No.
				A	B	C					
				FP-20L 120V1500W	DTJ	120					

G17q-7 GX17q-7, GY17q-7 Base

勝特力材料 886-3-5753170
 勝特力电子(上海) 86-21-54151736
 勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)

Lamp Type	ANSI	Rated Voltages (V)	Power Consumption (W)	Outside Dimension			Total Lumen (lm)	Color Temp (K)	Avg Life (H)	Filament	Fig.No.	Base
				A	B	C						
				FP-TF/10 24V150W	CYN	24						
FP-TF/10 120V150W	BEH	120	150	32	79	33.4	3500	3100	15	CC-13	12	G17 q-7
FP-TFM/10 120V150W	CAR	120	150	32	80	33.4	-	3100	15	CC-13 Prox.Ref.	13	G17 q-7
FP-TFR/12G 120V150W	CFG	120	150	38	90.5	39.7	-	3150	15	CC-6 Ballasted	14	GY17 q-7
FP-TFR/12L 21V150W	DCA	21	150	38	90.5	39.7	-	3250	15	CC-6	16	GY17 q-7
FP-TF/10 220/230V150W	CTD	220/230	150	28.5	79	33.4	3000	3000	25	CC-13	12	GY17 q-7
FP-TF/10 100/120V300W	CWD	100/120	300	32	103	39.7	7400	3150	25	C-13	12	GY17 q-7
FP-TFM/10 120V300W	CAL	120	300	32	103	39.7	-	3150	25	C-13 Prox Ref.	13	GY17 q-7
FP-TFM/10 H5 120V300W	CRT	120	300	32	103	39.7	-	2900	500	C-13D Prox.Ref.	13	GY17 q-7
FP-TF/10 220/230V300W	CSF	220/230	300	32	103	39.7	6600	3050	25	CC-13	12	GY17 q-7
FP-TFM/10 220/250V300W	CXH	220/250	300	32	103	39.7	-	3100	25	CC-13 Prox.Ref.	13	GY17 q-7
FP-TF/10 120V400W	DAT	120	400	32	103	39.7	10000	3200	25	C-13D	12	GY17 q-7
FP-TF/10 100/120V500W	DAK/DAY	100/120	500	32	103	39.7	12500	3200	25	C-13D	12	GY17 q-7
FP-TFM/10 120V 500W	CZA/CZB	120	500	32	103	39.7	-	3200	25	C-13D Prox.Ref.	13	GY17 q-7
FP-TFM/12 HS 120V500W	DEK/DFW	120	500	38	89	44.5	-	3200	25	C-13D Prox.Ref.	15	GY17 q-7
FP-TFM/12 H2 120V500W	DAH	120	500	38	101.6	44.5	-	3000	200	C-13D Prox.Ref.	15	GY17 q-7
FP-TF/12 120V750W	DEP/DGR	120	750	38	117	39.7	19500	3200	25	C-13D	12	GY17 q-7
FP-TFM/12 120V750W	CWA	120	750	38	117	39.7	-	3200	25	C-13D Prox.Ref.	13	GY17 q-7
FP-TFM/12 HS										C-13D		GY17

120V750W	DLN	120	750	38	95.3	44.5	-	3200	25	Prox.Ref.	15	q-7
FP-TFM/12										C-13D		GY17
120V1000W	CTT/DAX	120	1000	38	117	39.7	-	3250	25	Prox.Ref.	13	q-7

勝特力材料 886-3-5753170
勝特力电子(上海) 86-21-54151736
勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)