

JC

Optical - Single Coil

image



勝特力材料 886-3-5753170
 勝特力电子(上海) 86-21-54151736
 勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)

G4 Base

Lamp Type	ANSI	Rated Voltages (V)	Power Consumption (W)	Outside Dimension			Total Lumen (lm)	Color Temp (K)	Avg Life (H)	Filament	Fig.No.
				A	B	C					
JC 6V 10W/M	ESA/FHD	6	10	9	30	19.5	200	3200	100	C-6	1
JC 6V 20W/M	ESB/FHE	6	20	9	30	19.5	450	3200	100	C-6	1
JC 12V 23W/M		12	23	9	30	19.5	500	3200	100	C-6	1

G5.3 Base

Lamp Type	ANSI	Rated Voltages (V)	Power Consumption (W)	Outside Dimension			Total Lumen (lm)	Color Temp (K)	Avg Life (H)	Filament	Fig.No.
				A	B	C					
DZA 10.6V 30W	DZA	10.8	30	11.5	51	27	600	3100	400	C-6	2
FHR 12V 50W	FHR	12	50	11.5	51	29.4	1400	3300	50	CF-6	2
ELA 19V 65W	ELA	19	65	11.5	45	25.4	1900	3350	25	CC-6	2
DYT 19V 80W	DYT	19	80	11.5	51	27	2600	3350	25	CF-6	2
GCC 12V 100W	GCC	12	100	11.5	57	32	2900	3300	200	CF-6	2
DZB 12V 100W	DZB	12	100	11.5	51	27	3100	3400	50	CF-6	2
DYF19.3V140W	DYF	19.3	140	11.5	51	27	4000	3200	50	CF-6	2
FGF 24V 150W	FGF	24	150	13.5	54	27	5000	3400	50	CF-6	2
EML 24V 175W	EML	24	175	13.5	57	27	5600	3200	125	CF-6	2

G6.35,G6.35 Ceramic Cover Base

Lamp Type	ANSI	Rated Voltages (V)	Power Consumption (W)	Outside Dimension			Total Lumen (lm)	Color Temp (K)	Avg Life (H)	Filament	Fig.No.
				A	B	C					

JC 12V 20W		12	20	11.5	44	30	480	3150	50	C-6	4
JC 6V 30W		6	30	11.5	44	28	690	3200	100	CF-6	4
JC 12V 30W		12	30	11.5	44	30	800	3200	50	CF-6	4
JC 12V 35W		12	35	11.5	40	30	600	2900	1000	CF-6	4
JC 6V 40W		6	40	11.5	44	30	900	3200	50	C-6	4
JC 12V 40W		12	40	11.5	44	30	900	3200	50	CF-6	4
JC 12V 50W	BRL/BCD	12	50	11.5	44	30	1600	3300	50	CF-6	4
JC 12V 50W/H20V		12	50	11.5	44	30	950	3000	2000	C-8	4
JC 12V 50W/H20		12	50	11.5	44	30	850	3000	2000	CF-6	4
JC 12V 75W		12	75	11.5	44	30	2000	3300	50	CF-6	4
JC 24V100W/H20		24	100	11.5	44	30	1950	2900	2000	CF-6	4
JC 15V 150W	EVB/BRJ	15	150	11.5	44	30	5000	3400	50	CF-6	4
JC 24V 150W/H20		24	150	13.5	50	30	3300	3025	2000	CF-6	4
JC 24V 150W/H5		24	150	13.5	50	32	4200	3200	500	CF-6	4
JC 24V 150W/H3		24	150	13.5	50	32	4500	3300	300	CF-6	4
JC 24V 150W	FCS	24	150	13.5	50	32	5000	3400	50	CF-6	4
JC 24V 150W/H10	FHY	24	150	13.5	50	30	3700	3100	1000	CF-6	4
FDV 24V 150W	FDV	24	150	13.5	50	30	4300	3300	100	CF-6	4
FDW 24V 150W	FDW	24	150	13.5	50	30	5000	3400	50	CF-6	5
JC 16V 160W		16	160	11.5	44	30	4900	3400	20	CF-6	4
JC 24 250W/H2		24	250	13.5	55	33	7400	3300	200	CF-6	4
JC 24V 250W	EHJ	24	250	13.5	55	33	8500	3400	50	CF-6	4
JC 25V 250W		25	250	13.5	56	33	8500	3400	50	CF-6	4
FNT 24V 275W	FNT	24	275	13.5	55	33	10000	3400	75	CF-6	4
EDV 36V 400W	EVD	36	400	18	60	36	16000	3450	50	CF-6	4

勝特力材料 886-3-5753170
 勝特力电子(上海) 86-21-54151736
 勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)

勝特力材料 886-3-5753170
 勝特力电子(上海) 86-21-54151736
 勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)

GX6.35 Base

Lamp Type	ANSI	Rated Voltages (V)	Power Consumption (W)	Outside Dimension			Total Lumen (lm)	Color Temp (K)	Avg Life (H)	Filament	Fig.No.
				A	B	C					
JC 12V 50W/L		12	50	11.5	60	36	1300	3300	50	CF-6	8
JC 12V 100W/L		12	100	11.5	60	37	3200	3300	50	CF-6	8
JC 24V 100W/L		24	100	11.5	60	36	2900	3300	50	CF-6	8
JC 12V 130W/L		12	130	11.5	60	36	3700	3200	100	CF-6	8
JC 24V 150W/L		24	150	13.5	61	37	4800	3400	50	CF-6	8
JC 24V 150W H10/L		24	150	13.5	64	32	3450	3100	1000	CF-6	9
JC 16V 160W/L		16	160	11.5	60	36	4900	3400	20	CF-6	8
JC 24V 200WB/L		24	200	13.5	64	32	4400	3050	2000	CF-6	9
JC 24V 200WC/L		24	200	13.5	64	32	5500	3200	50	CF-6	9
JC 24V 250WL		24	250	13.5	63	37	8500	3400	50	CF-6	8
JC 24V 300W/L		24	300	13.5	60	36	9600	3400	50	CF-6	8

GY6.35,GY6.35 Ceramic Cover Base

Lamp Type	ANSI	Rated Voltages (V)	Power Consumption (W)	Outside Dimension			Total Lumen (lm)	Color Temp (K)	Avg Life (H)	Filament	Fig.No.
				A	B	C					
JC 12V 50W/H20/GY6.35		12	50	11.5	44	30	850	3000	2000	CF-6	6
JC 24V 50W		24	50	11.5	44	30	750	2900	2000	CC-6	6
FDX 12V 100W	FDX	12	100	11.5	44	30	3500	3300	50	CF-6	7
JC 12V 100WIH20	EVA	12	100	11.5	44	30	2400	3000	2000	CF-6	6
JC 12V 100W	FCR	12	100	11.5	44	30	3400	3300	50	CF-6	6
JC 24V 100W		24	100	11.5	44	30	2000	3000	2000	CC-6	6
JC 24V 300W		24	300	13.5	55	33	9900	3400	50	CF-6	6
JC 24V 300W L/2	FLW	24	300	13.5	55	33	10450	3500	50	CF-6	7

勝特力材料 886-3-5753170
勝特力电子(上海) 86-21-54151736
勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)

GY9.5 Base

Lamp Type	ANSI	Rated Voltages (V)	Power Consumption (W)	Outside Dimension			Total Lumen (lm)	Color Temp (K)	Avg Life (H)	Filament	Fig.No.
				A	B	C					
DDJ 10V 80W	DDJ	10	80	11.5	51	27	1700	3150	1000	CF-6	10
EYL 12V 100W	EYL	12	100	11.5	62	36.5	2900	3300	50	CF-6	10
FDT 12V 100W	FDT	12	100	11.5	57	27	2900	3300	50	CF-6	10
DDP 22V 132W	DDP	22	132	13.5	57	33.4	3900	3250	125	CF-6	10
JC 12V 150W C/C		12	150	13.5	60	36.5	4000	3300	50	CF-6	10
EKL 21V 150W	EKL	21	150	11.5	51	27	4650	3350	40	CC-6	10
DZE 24V 150W	DZE	24	150	13.5	57	33.4	4600	3350	100	CF-6	10
FDS 24V 150W	FDS	24	150	13.5	57	33.4	4450	3400	50	CF-6	10
DZM 24V 250W	DZM	24	250	13.5	60	33.4	8000	3400	50	CF-6	10
DYG 30V 250W	DYG	30	250	19.9	62	36.5	8000	3400	15	CF-6	10
JC 28V 300W C/C		28	300	15	60	36.5	9600	3400	50	CF-6	10

勝特力材料 886-3-5753170
勝特力电子(上海) 86-21-54151736
勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)




Fig.1




Fig.2




Fig.3




Fig.4




Fig.5




Fig.6




Fig.7




Fig.8




Fig.9




Fig.10