

 CLICK FOR BIG PICTURE G-12-250 2500W G-24-250 2500W G-48-250 2500W	 Radio	 Lamp	 Computer	 Karaoke
	 Massage	 TV	 Recorder	 Notebook
	 V8	 TV Game		

 CLICK FOR BIG PICTURE G-12-250 2500W G-24-250 2500W G-48-250 2500W	 Radio	 Lamp	 Computer	 Karaoke
	 Massage	 TV	 Recorder	 Notebook
	 V8	 TV Game		

MODEL NO.	G-12-250	G-24-250
Output power continuous	2500W	2500W
Output power surge	5000W	5000W
Over load	2501-3000W	2501-3000W
AC Output voltage	100V or 110V or 115V or 120V or 220V or 230V or 240V	
Output wave form	Modified Sine	Modified Sine Wave

	Wave phase corrected	phase corrected
Frequency +/-1%	60Hz 50Hz	60Hz 50Hz
DC input voltage	10-15V	20-30V
Low battery alarm	audible,10.7 VDE	audible,21.5VDC
Low battery cutout	10 VDC	20 VDC
Efficiency	approx, 85-90%	approx, 85-90%
Over temperature protection	55°C+/-5°C	55°C+/-5°C
No load current draw		
switch ON	<0.6 ADC	<0.5 ADC
switch OFF	<0.2 mADC	< 0.2 mADC
Dimensions (LXWXH)	496 X 203 x 166mm	496 X 203 X 166 mm
Net weight	9 KGS(approx.)	9 KGS(approx.)

勝 特 力 材 料 886-3-5753170
 勝特力电子(上海) 86-21-54151736
 勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)