


勝特力材料 886-3-5753170
勝特力电子(上海) 86-21-54151736
勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)

·型號說明



項次	代號	說明
1. 固定孔徑	T2	Φ22mm/ Φ25mm
	T3	Φ30mm
2. 型式	IS	標準選擇
	IH	長柄選擇
3. 外型	R	圓型
	S	方型
4. 動作方式	1	二段 45°
	2	二段 90°
	3	二段 45°復歸
	4	三段 45° x2
	5	三段 45° x2 右邊復歸
	6	三段 45° x2 左邊復歸
	7	三段 45° x2 二邊復歸
項次	代號	說明
5. 電壓	1	110VAC (霓虹燈泡)
	2	220 " (")
	3	380 " (")
	4	440 " (")
	5	6V " (鎢絲燈泡)
	6	18V " (")
	7	24V " (")
	8	30V " (")
	9	12V " (")
6. 顏色	R	紅

7.接點數目	G	綠	
	O	橙	
	W	白	
	BL	藍	
8.接點種類	1-3	1-3	
	A	二段	三段
	B	1a	-
	C	1b	-
		1a1b	1a01a

·直接式照光選擇開關二段接點圖

型式	TC-I1A	TC0I1B	TCI1C2	TC-I2A	TC-I2B	TC-I2C2																																																						
接點	1a	1b	1a1b	2a	2b	2a2b																																																						
接點圖	<table border="1"> <tr><td>contact</td><td>0</td><td>1</td></tr> <tr><td>13-14</td><td></td><td>x</td></tr> </table>	contact	0	1	13-14		x	<table border="1"> <tr><td>contact</td><td>0</td><td>1</td></tr> <tr><td>11-12</td><td>x</td><td></td></tr> </table>	contact	0	1	11-12	x		<table border="1"> <tr><td>contact</td><td>0</td><td>1</td></tr> <tr><td>11-12</td><td>x</td><td></td></tr> <tr><td>23-24</td><td></td><td>x</td></tr> </table>	contact	0	1	11-12	x		23-24		x	<table border="1"> <tr><td>contact</td><td>0</td><td>1</td></tr> <tr><td>13-14</td><td></td><td>x</td></tr> <tr><td>23-24</td><td></td><td>x</td></tr> </table>	contact	0	1	13-14		x	23-24		x	<table border="1"> <tr><td>contact</td><td>0</td><td>1</td></tr> <tr><td>11-12</td><td>x</td><td></td></tr> <tr><td>21-22</td><td>x</td><td></td></tr> </table>	contact	0	1	11-12	x		21-22	x		<table border="1"> <tr><td>contact</td><td>0</td><td>1</td></tr> <tr><td>11-12</td><td>x</td><td></td></tr> <tr><td>13-14</td><td></td><td>x</td></tr> <tr><td>21-22</td><td>x</td><td></td></tr> <tr><td>23-24</td><td></td><td>x</td></tr> </table>	contact	0	1	11-12	x		13-14		x	21-22	x		23-24		x
contact	0	1																																																										
13-14		x																																																										
contact	0	1																																																										
11-12	x																																																											
contact	0	1																																																										
11-12	x																																																											
23-24		x																																																										
contact	0	1																																																										
13-14		x																																																										
23-24		x																																																										
contact	0	1																																																										
11-12	x																																																											
21-22	x																																																											
contact	0	1																																																										
11-12	x																																																											
13-14		x																																																										
21-22	x																																																											
23-24		x																																																										

·直接式照光選擇開關三段接點圖

型式	TC-I1C3	TC-I2C3																												
接點	1a01a	2a02a																												
接點圖	<table border="1"> <tr><td>contact</td><td>1</td><td>0</td><td>2</td></tr> <tr><td>13-14</td><td>x</td><td></td><td></td></tr> <tr><td>23-24</td><td></td><td></td><td>x</td></tr> </table>	contact	1	0	2	13-14	x			23-24			x	<table border="1"> <tr><td>contact</td><td>1</td><td>0</td><td>2</td></tr> <tr><td>13-14</td><td>x</td><td></td><td></td></tr> <tr><td>23-24</td><td></td><td></td><td>x</td></tr> <tr><td>23-24</td><td></td><td></td><td>x</td></tr> </table>	contact	1	0	2	13-14	x			23-24			x	23-24			x
contact	1	0	2																											
13-14	x																													
23-24			x																											
contact	1	0	2																											
13-14	x																													
23-24			x																											
23-24			x																											