



勝特力材料 886-3-5753170
 勝特力电子(上海) 86-21-54151736
 勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)



項次	代號	說明
1. 固定孔徑	T2	Φ 22mm/ Φ25mm
	T3	Φ 30mm
2. 型式	TS	標準選擇
	TH	長柄選擇
3. 外型	R	圓型
	S	方型
4. 動作方式	1	 二段 45°
	2	 二段 90°
	3	 二段 45° 復歸
	4	 三段 45°x2
	5	 三段 45°x2 右邊復歸
	6	 三段 45°x2 左邊復歸
	7	 三段 45°x2 二邊復歸
5. 電壓 (50-60HZ)	1	110/5VAC
	2	220/5VAC
6. 顏色	R	紅
	G	綠
	O	橙
	W	白
	BL	藍
7. 接點數目	1-2	1-2 組
8. 接點種類	A	二段 三段
	B	1a -
	C	1b - 1a1b 1a01a

·照光式選擇開關二段接點圖

型式	TC-T1A	TC-T1B	TC-T1C2	TC-T2A	TC-T2B	TC-T2C2
接點	1a	1b	1a1b	2a	2b	2a2b

接點圖																																																												
	<table border="1"> <tr><td>contact</td><td>0</td><td>1</td></tr> <tr><td>23-24</td><td></td><td>x</td></tr> </table>	contact	0	1	23-24		x	<table border="1"> <tr><td>contact</td><td>0</td><td>1</td></tr> <tr><td>11-12</td><td>x</td><td></td></tr> </table>	contact	0	1	11-12	x		<table border="1"> <tr><td>contact</td><td>0</td><td>1</td></tr> <tr><td>11-12</td><td>x</td><td></td></tr> <tr><td>23-24</td><td></td><td>x</td></tr> </table>	contact	0	1	11-12	x		23-24		x	<table border="1"> <tr><td>contact</td><td>0</td><td>1</td></tr> <tr><td>13-14</td><td></td><td>x</td></tr> <tr><td>23-24</td><td></td><td>x</td></tr> </table>	contact	0	1	13-14		x	23-24		x	<table border="1"> <tr><td>contact</td><td>0</td><td>1</td></tr> <tr><td>11-12</td><td>x</td><td></td></tr> <tr><td>21-22</td><td>x</td><td></td></tr> </table>	contact	0	1	11-12	x		21-22	x		<table border="1"> <tr><td>contact</td><td>0</td><td>1</td></tr> <tr><td>11-12</td><td>x</td><td></td></tr> <tr><td>13-14</td><td></td><td>x</td></tr> <tr><td>21-22</td><td>X</td><td></td></tr> <tr><td>23-24</td><td></td><td>x</td></tr> </table>	contact	0	1	11-12	x		13-14		x	21-22	X		23-24		x
	contact	0	1																																																									
	23-24		x																																																									
	contact	0	1																																																									
	11-12	x																																																										
contact	0	1																																																										
11-12	x																																																											
23-24		x																																																										
contact	0	1																																																										
13-14		x																																																										
23-24		x																																																										
contact	0	1																																																										
11-12	x																																																											
21-22	x																																																											
contact	0	1																																																										
11-12	x																																																											
13-14		x																																																										
21-22	X																																																											
23-24		x																																																										

·照光式選擇開關三段接點圖

型式	TC-T1C3	TC-T2C3																								
接點	1a01a	2a02a																								
接點圖	<table border="1"> <tr><td>contact</td><td>1</td><td>0</td><td>2</td></tr> <tr><td>13-14</td><td>x</td><td></td><td></td></tr> <tr><td>23-24</td><td></td><td></td><td>x</td></tr> </table>	contact	1	0	2	13-14	x			23-24			x	<table border="1"> <tr><td>contact</td><td>1</td><td>0</td><td>2</td></tr> <tr><td>13-14</td><td>x</td><td></td><td></td></tr> <tr><td>23-24</td><td></td><td></td><td>x</td></tr> </table>	contact	1	0	2	13-14	x			23-24			x
contact	1	0	2																							
13-14	x																									
23-24			x																							
contact	1	0	2																							
13-14	x																									
23-24			x																							

勝特力材料 886-3-5753170
 勝特力电子(上海) 86-21-54151736
 勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)