

# Nieaf Instruments VoltPointer 非接觸式活線檢知器

The VoltPointer has equal functionality to the VoltSafe; it is a voltage detector and non-voltage indicator.

The detector is always activated and will automatically give a (red) optical and an acoustic signal upon the presence of voltage. The VoltPointer can be set manually to indicate a voltage free surrounding by a green LED in the partly transparent tip.



Inside the tip of the VoltPointer, a bright LED is positioned which can be switched on manually for use as a (small) flashlight. This makes the VoltPointer very suitable for use in poorly lit locations such as switch boards, distribution boxes, etc.

勝特力材料 886-3-5753170  
 勝特力电子(上海) 86-21-54151736  
 勝特力电子(深圳) 86-755-83298787  
[Http://www.100y.com.tw](http://www.100y.com.tw)

Specifications	
Voltage range	100 - 1000 V AC
Frequency	45 - 65 Hz
Power supply	2x AAA, 1.5V battery
Overvoltage category	IP 64
Overvoltage category	CAT III/1000V - CAT IV/600V
Standard	EN 61010-1
Dropproof	1 meter
Dimensions	128 x 21 mm.
Weight	approx. 60 gram
Art.no.	626 000 663
Including	Manual and batteries

功能	型號	VoltBeeper	VoltPointer
照明 LED 燈		×	●
檢知電池電力按鍵		×	●
閃爍 LED		●	●
蜂鳴聲		●	●
電壓範圍(100-1000VAC)		●	●
適用頻率(45-65Hz)		●	●
過電壓總類(CAT III 1000V/CAT IV 600V)		●	●
認證規範(EN61010-1)		●	●
保護等級(IP64)		●	●
尺寸(LxWxH)		138x22x16mm	128x28x16mm
淨重(g)		50	60
電源供應 2xAAA		●	●

## 特點：

- ◆ 可安全檢查出電線、保險絲(座)、插座、斷路器、接線盒等待測物之活線
- ◆ 可檢知電壓範圍從 100V~1000VAC(規範安全電壓值)，IP64 保護等級
- ◆ 具電池電力有無之測試鍵，檢隻電壓時會發出持續蜂鳴聲及 LED 紅光閃爍
- ◆ 具夜間照明燈功能